

Jax Chandelier

EC10310, EC10312 | 1.1

GENERATION LIGHTING

Chandelier

GENERAL PRODUCT INFORMATION:

These fixtures are intended to be installed utilizing NEC compliant junction boxes.

This product is safety listed for damp locations.


Incandescent lamps may be dimmed with a standard incandescent dimmer. LED lamps may be dimmed with a LED dimmer. Consult lamp manufacturer for additional information.

This instruction shows a typical installation.

CAUTION - RISK OF FIRE

This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.

Use minimum 90°c supply conductors.



- 1** Screw the half ball to the stem which will be on top.
- 2** **Install the Arms:** To prevent the wires from being twisted inside the center hub:
 - A)** Push the excess wire near the hole.
 - B)** Turn the arm counterclockwise about 5 times.
 - C)** Fasten the arm in place. When installing the arms, grasp the arms. **Do not grasp the socket cups.**
- 3** Determine the wanted height or look of the fixture with the provided stems, then assemble them by screwing them together.
- 4** Feed the fixture wires through the stem assembly, then screw the stem assembly to the top of the fixture.
- 5** Feed the fixture wires through collar nut, canopy and the half ball assembly, then screw the half ball assembly onto the stem assembly.
- 6** Align and secure the mounting plate to the junction box, then slide the half ball assembly onto the stem assembly.
- 7** Connect the fixture to a suitable ground in accordance to local electrical codes.
- 8** Connect the white fixture wire (square and/or rigid) to the neutral power line wire with a wire nut.
- 9** Connect the black fixture wire (round and/or smooth) to the hot power line wire with a wire nut.
- 10** Neatly place all the wires into the junction box, place the canopy onto the mounting plate and secure it in place by screwing the collar nut tightly onto the mounting plate.
- 11** Screw the lamps into the sockets. Refer to the label on the socket for Max Wattage Information.

SAVE THESE INSTRUCTIONS!

GENERATION LIGHTING

7400 Linder Ave, Skokie, IL 160077

800.969.3347

www.generationlighting.com

© 2019 Generation Lighting. All rights reserved.

The "Generation Lighting" graphic is a registered trademark of Generation Lighting. Generation Lighting reserves the right to change specifications for product improvements without notification.