

## **ASSEMBLY INSTRUCTIONS**







Item # TOB 2502

WE RECOMMEND INSTALLATION OF THIS LIGHTING FIXTURE BE DONE BY A LICENSED ELECTRICIAN.

WARNING \*\*\* SWITCH OFF THE MAIN ELECTRICAL SUPPLY FROM THE MAIN FUSE BOX/CIRCUIT BREAKER BEFORE INSTALLATION.

INSPECT ITEM CAREFULLY BEFORE ATTEMPTING TO INSTALL. IF THERE IS ANY DAMAGE OR OBVIOUS DEFECT, DO NOT INSTALL.

## ITEM MAY NOT BE RETURNED ONCE IT HAS BEEN INSTALLED.

- Carefully remove all parts from the carton.
- 2. Remove mounting plate (A) from base of light fixture (D) by removing base screws (C).
- 3. Affix mounting plate (A) to wall outlet box with mounting screws (B) provided.
- Attach ground (green or green/yellow) wire to ground wire from wall outlet box (usually green or copper in color ), fasten both together with a plastic wire connector. Tightly wrap the wire connector with electrical tape, so the end of the connector is sealed. IT IS IMPERATIVE THAT THE OUTLET BOX IN YOUR HOME BE PROPERLY GROUNDED.
- 5. Connect both neutral (white ) fixture wire coming from fixture base to neutral (usually white ) outlet wire. Fasten both wires together with a plastic wire connector and tightly wrap the wire connector with electrical tape.
- 6. Repeat the same procedure with the hot (black) wires. Always make sure that no wire strands Ireeft outside the connectors. DO NOT REVERSE THE HOT AND NEUTRAL CONNECTIONS OTHERWISE SAFETY WILL BE COMPROMISED.
- 7. Attach fixture base (D) to the affixed mounting plate (A) and secure with base screws (C).
- 8. Slide the center bracket of glass shade (F) onto the socket cover (E).
- 9. Insert light bulb (not included) into the socket.
- Restore power and test fixture. Installation is complete.









<sup>\*\*\*</sup> Clean with a dry, soft cloth only. Use no harsh abrasives or chemical agents.